



AC Resonance Test Set



Application

It is mainly used for cable, main transformer neutral point, GIS, Switches whose rated voltage not more than 110kv and other AC high voltage withstand test. The equipment consists of variable frequency power supply, excitation transformers, reactors, capacitive voltage divider

Technical Specification

Power supply	380V $\pm$ 10% , three – phase 50Hz/60Hz
Rated voltage output	0~1000KV
Max. output capacity	0~6400KVA
Test frequency range	30 ~ 300HZ
Continuous duty cycle	60min
Quality factor	30 ~ 80
Frequency setting resolution	0.1HZ
Test voltage waveform	Sine wave, waveform deviation factor : $\leq$ 1%
Temperature	0~50°C
Humidity	$\leq$ 90%RH

Note :

Due to keeping innovation,the specification and Machine pictures or color are subject to alteration without notice!